



LIGHTING

24x15W RGBW LED BATTERY WASHER



www.soundlightspain.com

Channel Mode

Channel	value	Function	Description
1	0-255	Master Dimmer	All colours 0-100%
2	0-255	Red intensity	Red 0-100%
3	0-255	Green intensity	Green 0-100%
4	0-255	Blue intensity	Blue 0-100%
5	0-255	White intensity	White 0-100%
6	0-255	Colours	Built - in colours
7	• 0-9 • 18-180 • 181-255	Strobe	• Strobe off • Strobe 1 • Strobe 2
8	0-9	No function	
	10-50	Auto	Jump effect
	51-100	Auto	Fade effect
	101-150	Auto	Pulse variation effect
	151-200	Auto	Combination effect
	201-255	_No function	
9	0-255	Auto speed	From slow to last

Display:

MENU

DOWN

UP

ENTER

- To select the programming functions
- To go backward in the selected functions
- To go forward in the selected functions,
- To confirm the selected functions

Menu Description

Level 1	Level 2	Level 3	Description
DMX Setting	DMX address	000-512	DMX Address Setting
	Channel	9ch	9 channel DMX mode
	W-DMX Setting	On/Off	Turn Wireless DMX on or off
	W-DMX Pairing	Unpair	
	Channel List	9ch	9 channel DMX mode list
	Display Sleep		Open/10s/20s/30s

System Setting	Power Setting	High	
		Normal	
		ECO	
	Button Lock	On/Off	Unlock:press/button up>down>up>down>enter
	Lost DMX	Clear	Black out the unit when DMX signal is lost
		Hold	Maintain the last setting when DMX signal is lost.
	IRC Setting	On/Off	
	Emergency	On/Off	
	Reset	Yes/No	Reset all settings to factory defaults
Manual Control	Manual dimming	R/G/B/W /A/ UV	all colour manual dimmer (0-255)
		Strobe	Master strobe speed(0-99)
	Static Colour	C1-C36	Select static colour mode
	Auto	Jump	Colour Jump mode. Adjustable speed (0-99)
		Fade	Colour Fade mode. Adjustable speed (0-99)
		Pulse	Colour Pulse mode. Adjustable speed (0-99)
			Combination of Jump, Fade and Pulse. Adjustable speed (0-99)
	Timer		Setting start and end times of static colour or Auto
	Clear		Clear manual dimmer value to 000
	User color		Custom Colors
	User run		Run the custom colors
	Work time		Working time of the model
	Temp		Display current temperature

Information	Version		Version number
	RDM UID		



Móvil: +34 638 626 631

www.soundlightspain.com